

AR-M350/450 & AR-P350/450

Paper Input & Output Tray Selection

PCL Paper Tray Selection Commands

Esc&10H	Pick from current paper source
Esc&17H	Pick from default tray
Esc&11H	Pick from tray 1
Esc&14H	Pick from tray 2
Esc&15H	Pick from tray 3
Esc&120H	Pick from tray 4
Esc&122H	Pick from Large Capacity tray
Esc&18H	Pick from Bypass

PJL Paper Tray Selection Commands

@PJL SET MEDIASOURCE=AUTO	Pick from Default Tray, or tray with correct paper size
@PJL SET MEDIASOURCE=TRAY1	Pick from Tray 1
@PJL SET MEDIASOURCE=TRAY2	Pick from tray 2
@PJL SET MEDIASOURCE=TRAY3	Pick from tray 3
@PJL SET MEDIASOURCE=TRAY4	Pick from tray 4
@PJL SET MEDIASOURCE=LCC	Pick from Large Capacity Cassette
@PJL SET MEDIASOURCE=MANUALFEED	Pick from Bypass

Postscript Paper Tray Selection Commands

Auto: <</DeferredMediaSelection true /MediaPosition 9 /ManualFeed false >> setpagedevice
Tray 1: <</DeferredMediaSelection true /MediaPosition 0 /ManualFeed false >> setpagedevice
Tray 2: <</DeferredMediaSelection true /MediaPosition 1 /ManualFeed false >> setpagedevice
Tray 3: <</DeferredMediaSelection true /MediaPosition 4 /ManualFeed false >> setpagedevice
Tray 4: <</DeferredMediaSelection true /MediaPosition 5 /ManualFeed false >> setpagedevice
LCT: <</DeferredMediaSelection true /MediaPosition 7 /ManualFeed false >> setpagedevice
Bypass: <</DeferredMediaSelection true /MediaPosition 3 /ManualFeed false >> setpagedevice

PJL Paper Output Selection Commands

@PJL SET OUTTRAY=TRAY1	Top Tray
@PJL SET OUTTRAY=TRAY2	Job Separator tray, or Saddle Stitch Offset
@PJL SET OUTTRAY=TRAY3	Saddle Stitch Tray
@PJL SET OUTTRAY=TRAY4	Finisher Top Bin, or Mail box Top Bin
@PJL SET OUTTRAY=TRAY5	Finisher Offset, or Mail box Bin 1
@PJL SET OUTTRAY=TRAY6	Mail box Bin 2
@PJL SET OUTTRAY=TRAY7	Mail box Bin 3
@PJL SET OUTTRAY=TRAY8	Mail box Bin 4
@PJL SET OUTTRAY=TRAY9	Mail box Bin 5
@PJL SET OUTTRAY=TRAY10	Mail box Bin 6
@PJL SET OUTTRAY=TRAY11	Mail box Bin 7

Other PJL Commands

@PJL SET RET=ON	select edge enhancement ON/OFF. Default ON
@PJL SET JOBSTAPLE=STAPLENON	select stapling, only available with finisher option fitted. STAPLENON/STAPLELEFT/ STAPLEBOTH/SADDLE
@PJL SET JOBBOOKLET=OFF	select pamphlet mode, ON/OFF.
@PJL SET ORIENTATION=PORTRAIT	PORTRAIT/LANDSCAPE
@PJL SET DUPLEX=OFF	select duplex ON/OFF. Default OFF
@PJL ENTER LANGUAGE=PCL	set language, forces interpreter into one mode. Stops problems of non recognition of job language type. PCL/PCLXL/POSTSCRIPT

Standard PCL Commands

Esc&10S	Simplex
Esc&11S	Duplex, long edge binding
Esc&12S	Duplex, short edge binding